

## **QUICK START**

The wireless pak originally broadcasts its name as "eb101". You can change the name of your pak and it will persist until you change it again.

Your PC will see your pak as an available device and let you add it. The default passkey is "0000". You generally only need to do this once. The pak will pair with your PC's bluetooth stack and a new COM port will be added for establishing communications automatically. That is, when the PC opens and sends data over the COM port, the wireless pak will automatically go into data communications mode.

To best understand your pak:

- **The onboard bluetooth radio remembers its baud rate when the power is turned off.**
- **The onboard 6551 ACIA does not remember its baud rate when the power is off.**
- **The bluetooth radio and the 6551 ACIA must be set to the SAME BAUD RATE in order to communicate or process commands**
- **Your first out-of-the-box communication with the pak must be at 9600 bps. You can then change the baud rate to a higher or lower setting.**

With the CoCo power OFF, insert the pak, and turn the CoCo on.

Type **EXEC &HE010** to launch the firmware on a CoCo 3.

Type **EXEC &HC000** on a CoCo 1 or 2.

See the manuals for all available bluetooth commands.

Enjoy!